



# MJ-1400C

## 1D Wired Barcode Scanner

MJ-1400C is with USB Wired Connection. It's an effective barcode scanner because it has superdecoding ability, even blurry, incomplete 1D barcodes can be decoded. It has fast scanning speed, long transmission distance, a lightweight and durable appearance and comes with three types of indication; Beep, LED Light and Vibrate. It doesn't need install or download any software, drivers or apps, just plug and play easily.



### Barcode Configuration

Compatible with



WindowsXP



Windows7



Windows8



Windows10



Android



iOS

# Specifications

<b>Type</b>	1D Wired Barcode Scanner
<b>Interface</b>	USB
<b>Processor</b>	32-bit
<b>Operating Keys</b>	1 Key Total, Scan & Power Key
<b>Sensor</b>	752*480
<b>Resolution</b>	4mil
<b>Print Contrast Ratio</b>	30%
<b>Depth of Field</b>	6-30cm
<b>Code Type</b>	1D:Code128, EAN-13, EAN-8, Code39, UPC-A, UPC-E, Codabar, China post 25, Interleaved 2 of 5, ISBN/ISSN, Code 93, UCC/EAN-128, GS1 Databar, etc.
<b>Operation System</b>	iOS / Android / Windows
<b>Power</b>	5V1A
<b>Standby Power</b>	20mA
<b>Operating Current</b>	160mA
<b>Operating Temperature</b>	32°F- 122°F/ 0°C- 50°C
<b>Storage Temperature</b>	-4°F- 140°F/ -10°C- 50°C
<b>Humidity in Operation</b>	20%- 85% (Non-condensing)
<b>Humidity in Storage</b>	20%- 85% (Non-condensing)
<b>Dimensions (W x H x D)</b>	50mm x 140mm x 70mm
<b>Weight</b>	180g